



Project:	Туре:
Prepared By:	Date:

Driver Info	1	LED Info	
Type 120V	Constant Current 0.50A/0.41A/0.33A	Watts Color Temp	60/50/40W 5000K/4000K/3500K
208V 240V 277V Input Watts	0.29A/0.24A/0.19A 0.25A/0.21A/0.17A 0.22A/0.18A/0.14A 39.9-60.7W	Color Accuracy L70 Lifespan Lumens	84-85 CRI 50,000 Hours 5,854-8,986 lm
		Efficacy	140.2-158.5 lm/W

# **Technical Specifications**

# **Field Adjustability**

## Field Adjustable:

Field Adjustable Light Output: 60W/50W/40W (factory default 19W) Color temperature selectable by 5000K, 4000K and 3500K (factory default 4000K)

## Compliance

#### **UL Listed:**

Suitable for damp locations

#### IESNA LM-79 & LM-80 Testing:

RAB LED luminaires and LED components have been tested by an independent laboratory in accordance with IESNA LM-79 and LM-80.

#### **DLC Listed:**

This product is on the Design Lights Consortium (DLC) Qualified Products List and is eligible for rebates from DLC Member Utilities. Designed to meet DLC 5.1 requirements.

DLC Product Code: S-FP3EWO

#### **LED Characteristics**

#### LEDs:

Long-life, high-efficacy, discrete, surface-mount LEDs

## **Color Uniformity:**

RAB's range of Correlated Color Temperature follows the guidelines of the American National Standard for Specifications for the Chromaticity of Solid State Lighting (SSL) Products, ANSI C78.377-2017.

## **Color Consistency:**

4-step MacAdam Ellipse binning to achieve consistent fixture-to-fixture color

#### Performance

#### Lifespan:

50,000-Hour LED lifespan based on IES LM-80 results and TM-21 calculations

#### **Electrical**

# **Dimming Driver:**

Driver includes dimming control wiring for 0-10V dimming systems. Requires separate 0-10V DC dimming circuit. Dims down to 10%.

# THD:

7.52% at 120V, 7.96% at 277V

#### **Power Factor:**

99.38% at 120V, 94.72% at 277V

#### **Surge Protection:**

1kV+2kV

# **Battery Backup:**

Battery backup will operate the fixture for 90 minutes if power fails. Wired for 120-277V.

## **Battery Backup Light Loss Factor:**

60W: 0.0171 50W: 0.02 40W: 0.0247 SR8/E



# **Technical Specifications (continued)**

## Construction

#### **Cold Weather Starting:**

The minimum starting temperature is 0°C (32°F)

#### **Maximum Ambient Temperature:**

Suitable for use in up to 60°C (140°F)

#### Lens:

Polycarbonate lens

#### Housing:

Iron

#### Mounting:

Surface mounting standard. V-Hooks and Chain mounting available (ordered separately, SR VHOOK KIT).

#### **Green Technology:**

Mercury and UV free. RoHS-compliant components.

#### Finish:

Formulated for high durability and long-lasting color

## Other

#### 5 Yr Limited Warranty:

The RAB 5-year, limited warranty covers light output, driver performance and paint finish. RAB's warranty is subject to all terms and conditions found at <u>rablighting.com/warranty.</u>

#### **Accessories:**

Suspended Mounting Kit: SR VHOOK KIT Surface Mount Kit: SR JOIN KIT

#### Note

All values are typical (tolerance +/- 10%)

# **Buy American Act Compliance:**

RAB values USA manufacturing! Upon request, RAB may be able to manufacture this product to be compliant with the Buy American Act (BAA). Please contact customer service to request a quote for the product to be made BAA compliant.

# Dimensions State of the state

# Features

50,000-Hour LED lifespan

120-277V standard

0-10V dimming standard

**DLC Premium Listed** 

5-Year, limited warranty

SR8/E



Ordering Matrix								
Family	Size/Wattage	Color Temp	Mounting	Finish	Options			
SR	8				/E			
	2 = 2ft (19/14/10W) 4 = 4ft (40/30/20W) 8 = 8ft (60/50/40W)	Blank = 5000K/4000K/3500K Field Adjustable	<b>Blank</b> = J-Box Adaptor	<b>Blank =</b> White	Blank = No Option  /E = Battery Back Up  /MVS = Microwave Occupancy Sensor  /PIR = Passive Infrared Occupancy Sensor  /LCBS = Lightcloud Blue PIR Senor  /LCBS/MVS = Lightcloud Blue MVS Senor  /MVS/E = Microwave Occupancy Sensor w/  Battery Back Up  /PIR/E = Passive Infrared Occupancy Sensor w/  Battery Back Up  /LCBS/E = Lightcloud Blue PIR senor w/ Battery  Back Up  /LCBS/MVS/E = Lightcloud Blue MVS senor w/  Battery Back Up			