## SWISH34-2X4-29YN/LCS

# RAB



Proje	ect:	Туре:		
Prep	ared By:	Date:		
<b>Driver</b> Type	Info Constant Current	<b>LED Info</b> Watts	29W	

Driver Info			LED Info		
	Туре	Constant Current	Watts	29W	
	120V	0.25A	Color Temp	3500K (Warm	
	208V	0.14A	oolor romp	Neutral)	
	240V	0.12A	Color Accuracy	83 CRI	
	277V	0.11A	L70 Lifespan	60,000	
Input Watts 26.6W		Lumens	3,271		
			Efficacy	123 lm/W	

### **Technical Specifications**

#### Lightcloud

#### Lightcloud Sensor Installed:

Occupancy, vacancy, and closed loop daylight harvesting in one versatile sensor. In addition control any fixture in your Lightcloud integrated/embedded networked lighting luminaire-level control system. LLLC - capable of switching, 0-10Vdimming, power/energy monitoring. Can also be used to extend the range of the Lightcloud mesh network communication protocols. DLC system - N1XMLOEATBA Learn more about Lightcloud.

#### Listings

#### **UL Listed:**

Suitable for damp locations

#### **CCEA Compliant:**

Luminaire Requirements used in Environmental Air Space per the electrical code specification of the City of Chicago

#### IESNA LM-79 & IESNA LM-80 Testing:

RAB LED luminaires and LED components have been tested by an independent laboratory in accordance with IESNA LM-79 and LM-80.

#### Electrical

#### **Driver:**

Class 2, Constant Current, 120-277V, 50/60Hz, 120V: 0.25A, 208V: 0.14A, 240V: 0.12A, 277V: 0.11A

#### **Dimming Driver:**

Driver includes dimming control wiring for 0-10V dimming systems. Requires separate 0-10V DC dimming circuit. Dims down to 10%.

#### THD:

3.43% at 120V, 7.34% at 277V

#### **Power Factor:**

99.6% at 120V, 91.7% at 277V

#### Surge Protection:

2.5kV

#### Construction

#### **Cold Weather Starting:**

The minimum starting temperature is  $-20^{\circ}C$  ( $-4^{\circ}F$ )

#### **Ambient Temperature:**

Suitable for use in up to 40°C (104°F)

### IC Rated:

Suitable for direct contact with insulation

#### Housing:

Die-formed, 24-gauge, cold-rolled steel

#### Mounting:

Integral T-grid clips make installation easy and secure

#### Construction

#### **Reflector:**

Integral reflector (on the sides) with high reflectance finish, optimized for uniform distribution.

#### Lens:

Frosted polycarbonate

#### Finish:

Formulated for high durability and long-lasting color

#### **Green Technology:**

Mercury and UV free. RoHS-compliant components.

#### **LED Characteristics**

#### LEDs:

Long-life, high-efficacy, surface-mount LEDs

#### **Color Uniformity:**

RAB's range of Correlated Color Temperature follows the guidelines of the American National Standard for Specifications for the Chromaticity of Solid State Lighting (SSL) Products, ANSI C78.377-2017.

#### Performance

#### Lifespan:

60,000-Hour LED lifespan based on IES LM-80 results and TM-21 calculations

#### Other

#### Equivalency :

Equivalent to (2) F32T8

#### 5 Yr Limited Warranty:

The RAB 5-year, limited warranty covers light output, driver performance and paint finish. RAB's warranty is subject to all terms and conditions found at <u>rablighting.com/warranty</u>.

#### **Buy American Act Compliance:**


RAB values USA manufacturing! Upon request, RAB may be able to manufacture this product to be compliant with the Buy American Act (BAA). Please contact customer service to request a quote for the product to be made BAA compliant.

### Features

Optional surface and recessed mount kits available Optional programmable occupancy sensor for multi-level lighting control 0-10V dimming standard on all models 60,000-hour LED lifespan

5-Year, Limited Warranty

Dimensions





# SWISH34-2X4-29YN/LCS

#### **Ordering Matrix** Family Size Wattage **Color Temp** Options SWISH34 2X4 29 ΥN /LCS 2X2 = 2' x 2' **19** = 19W (2' x 2') N = 4000K (Neutral) Blank = No Option /E2 = Battery Backup **29 =** 29W (2' x 2', 2' x 4') YN = 3500K (Warm Neutral) **2X4 =** 2' x 4' $39 = 39W(2' \times 4')$ **/LC** = Lightcloud® Controller /LCS = Lightcloud® Sensor **/PIR =** Passive Infrared Occupancy Sensor /LC/E2 = Lightcloud® Controller w/ Battery Backup Backup /PIR/E2 = Passive Infrared Occupancy Sensor w/ Battery Backup