



S28602

LED 4W G9 120V 3000K DIM/CARD
4 watt; JCD LED; 3000K; G9 base; 120-130 volts; Carded

Features

- Solid State LED lighting
- High Efficacy
- Long life
- Dimmable

Silicon LED Replacements for Halogen G9 lamps.



S28602

Item Number	UPC	Voltage	Watts	Operating Frequency	Base	Lamp Code	Dimmable/Non-Dimmable
S28602	045923286025	120/130	4	50/60Hz	G9	LED 4W G9 120V 3000K DIM/CARD	Dimmable

Suggested Dimmers	Finish	MOL In Inches	MOD In Inches	Initial Lumens	Average Rated Hours	Kelvin Temp	Color
Compatible dimmers for S28602	Clear	2-3/8"	0-1/2"	480	25000	3000	Soft White

CRI	Beam Spread Deg	Pack	Package Type	RoHS Compliant	UL or ETL Listed	UL Classification
80	360	48/12	CD/1	Yes	Yes	cETLus - Damp Location Rated



National Toll-Free:
800.43.SATCO
(800.437.2826)
www.satco.com

Distribution Centers:
New York, Florida, Texas,
Washington, California,
Puerto Rico

Corporate Offices:
110 Heartland Blvd.,
Brentwood, NY 11717
800.437.2826 631.243.2022
Fax 631.243.2027

